

IRI.TX4VA

4-channel transmitter

Frequency	433,92 Mhz
Power supply	1 12V alkaline battery
Power usage when in use	18mA
Code combinations (ARC)	18.000.000.000
Oscillator type	SAW
Working temperature	-20°C to 70°C
Built-in antenna	
Dimensions	69 x 39 x 14mm



Converting type IRI.TX4VA - 4-channel transmitter

From ARC (standard) to combined or HCS



From ARC (standard) to combined

1. Hold down button 1 and 2 for 20 sec.
2. LED flickers **3 times**. This repeats 9 times intermittently.
3. LED remains on. Release within 3 sec max.



From combined to HCS

1. Hold down button 1 and 2 for 20 sec.
2. LED flickers **4 times**. This repeats 9 times intermittently.
3. LED remains on. Release within 3 sec max.



From HCS to ARC (standard)

1. Hold down button 1 and 2 for 20 sec.
2. LED flickers **2 times**. This repeats 9 times intermittently.
3. LED remains on. Release within 3 sec max.



BORMET

Your safe partner in access

✉ info@bambormet.be

☎ +32 11 31 26 56

📍 Ambachtstraat 1137, 3850 Nieuwerkerken, Belgium