




GS-500

Cellphone remote control

Supply voltage	10-24V 50 Hz/60Hz ~ 500mA max
	10-24V  500mA max
Idle consumption	To 50mA
Modem frequency	2G/3G - 900/1800 MHz
Number of outputs	2
Type of outputs	Relais; NO (normally-open) or NC (normally-closed) configurable
Negative inputs	2
Positive inputs	1
Low input value input	0... 16V  -0,8...- 0,4mA
High input value input	5... 50V  -0,17...- 1,7mA
Standard connection type	NO (normally-open)
IP code	IP20
Dimensions	87 x 107 x 29mm
Operating temperature	-20... +55°C
Humidity	0-90% RH @0... +40°C



Features

Easy parking control

The GS-500 control system is an excellent way to facilitate your (residential) parking control. Controlling the gate is done via a free voice command or via the app. A SIM card in the receiver registers incoming commands. Access opens only upon receiving registered users.

- Up to 2000 users + 5 administrators
- Operation via app or voice call
- Management via web platform/software or SMS

Event logging

The GS-500 has an internal memory to keep track of important events. The system can remember up to 1000 events. gebeurtenissen onthouden.

- When someone dialed in
- Who dialed in
- Who added a new user

Managing user rights

Users can be divided into 4 different groups, each with different specifications.

1. Full access
2. Limited access: on weekdays only
3. Limited access with time frame: based on date and time
4. Limited number of accesses per person: e.g. max. 10

SIM cards

The GS-500 works with both pre-paid SIM cards, and subscription SIM cards. Contact with the GS-500 is free of charge. For frequent use, we recommend a subscription SIM card.

Your safe partner in access



BORMET

Your safe partner in access

✉ info@bambormet.be

☎ +32 11 31 26 56

📍 Ambachtstraat 1137, 3850 Nieuwerkerken, Belgium